DuroMax Inverter Comparison Chart









	XP16000iHT	XP16000iH	XP11000iHT	XP11000iH	XP9500iH	XP7000iH	XP2300iH
Fuel Type	Gasoline Propane Natural Gas	Gasoline Propane	Gasoline Propane Natural Gas	Gasoline Propane	Gasoline Propane	Gasoline Propane	Gasoline Propane
Peak Wattage	16,000 Watts (Gas) 15,200 Watts (LP) 13,800 Watts (NG)	16,000 Watts (Gas) 15,200 Watts (LP)	11,000 Watts (Gas) 11,450 Watts (LP) 9,500 Watts (NG)	11,000 Watts (Gas) 10,450 Watts (LP)	9,500 Watts (Gas) 9,025 Watts (LP)	7,000 Watts (Gas) 6,650 Watts (LP)	2,300 Watts (Gas) 2,150 Watts (LP)
Running Wattage	13,000 Watts (Gas) 12,350 Watts (LP) 11,200 Watts (NG)	13,000 Watts (Gas) 12,350 Watts (LP)	9,000 Watts (Gas) 8,550 Watts (LP) 7,700 Watts (NG)	9,000 Watts (Gas) 8,550 Watts (LP)	7,600 Watts (Gas) 7,200 Watts (LP)	5,500 Watts (Gas) 5,225 Watts (LP)	1,800 Watts (Gas) 1,700 Watts (LP)
Running Amps at 120V	108.33 Amps (Gas) 102.92 Amps (LP) 93.33 Amps (NG)	108.33 Amps (Gas) 102.92 Amps (LP)	75 Amps (Gas) 71.25 Amps (LP) 64.17 Amps (NG)	75 Amps (Gas) 71.25 Amps (LP)	63.33 Amps (Gas) 60 Amps (LP)	45.83 Amps (Gas) 43.54 Amps (LP)	15 Amps (Gas) 14.16 Amps (LP)
Running Amps at 240V	54.17 Amps (Gas) 51.46 Amps (LP) 46.66 Amps (NG)	54.17 Amps (Gas) 51.46 Amps (LP)	37.5 Amps (Gas) 35.63 Amps (LP) 32.08 Amps (NG)	37.5 Amps (Gas) 35.63 Amps (LP)	31.67 Amps (Gas) 30 Amps (LP)	22.92 Amps (Gas) 21.77 Amps (LP)	-
Outlets	50 Amp 240V (2) 120V GFCI (4)	50 Amp 240V (2) 120V GFCI (4)	50 Amp 120/240V (1) 30 Amp 120/240V (1) 20 Amp 120V GFCI (4)	50 Amp 120/240V (1) 30 Amp 120/240V (1) 20 Amp 120V GFCI (4)	50 Amp 120/240V (1) 30 Amp 120/240V (1) 20 Amp 120V GFCI (4)	30 Amp 120/240V (1) 20 Amp 120V GFCI (2)	30 Amp 120V (2) 20 Amp 120V (2)
Gasoline Runtime at 25% Load	18.2 Hrs	18.2 Hrs	18 Hrs	18 Hrs	21 Hrs	16 Hrs	13 Hrs
Gasoline Runtime at 50% Load	10.5 Hrs	10.5 Hrs	9 Hrs	9 Hrs	11 Hrs	8 Hrs	7 Hrs
Propane Runtime at 25% Load (40/60/100 lb. Tank)	11/16.5/27.75 Hrs	11/16.5/27.75 Hrs	16/24/40 Hrs	16/24/40 Hrs	19/28.5/47.5 Hrs	26/29/43.33 Hrs	38 Hrs (20 lb. Tank)
Propane Runtime at 50% Load (40/60/100 lb. Tank)	6/9.4/14.5 Hrs	6/9.4/14.5 Hrs	8/12/20 Hrs	8/12/20 Hrs	10/15/20.25 Hrs	14/21/23.33 Hrs	18 Hrs (20 lb. Tank)
Start Type	Remote Push Button	Remote Push Button	Remote Push Button Recoil	Remote Push Button Recoil	Remote Push Button Recoil	Remote Push Button Recoil	Recoil
Warranty	5 Years	5 Years	5 Years	5 Years	5 Years	5 Years	3 Years

DuroMax Generator Comparison Chart









	XP15000HXT+	XP15000HXT	XP15000HX	XP13000HXT	XP13000HX	XP13000EH	XP5500HX
Fuel Type	Gasoline Propane Natural Gas	Gasoline Propane Natural Gas	Gasoline Propane	Gasoline Propane Natural Gas	Gasoline Propane	Gasoline Propane	Gasoline Propane
Peak Wattage	15,000 Watts (Gas) 14,250 Watts (LP) 13,000 Watts (NG)	15,000 Watts (Gas) 14,250 Watts (LP) 12,825 Watts (NG)	15,000 Watts (Gas) 14,250 Watts (LP)	13,000 Watts (Gas) 12,500 Watts (LP) 11,250 Watts (NG)	13,000 Watts (Gas) 12,500 Watts (LP)	13,000 Watts (Gas) 12,500 Watts (LP)	5,500 Watts (Gas) 5,225 Watts (LP)
Running Wattage	12,000 Watts (Gas) 11,400 Watts (LP) 10,500 Watts (NG)	12,000 Watts (Gas) 11,400 Watts (LP) 10,260 Watts (NG)	12,000 Watts (Gas) 11,400 Watts (LP)	10,500 Watts (Gas) 10,000 Watts (LP) 9,000 Watts (NG)	10,500 Watts (Gas) 10,000 Watts (LP)	10,500 Watts (Gas) 10,000 Watts (LP)	4,500 Watts (Gas) 4,275 Watts (LP)
Running Amperage at 120V	100 Amps (Gas) 95 Amps (LP) 85.5 Amps (NG)	100 Amps (Gas) 95 Amps (LP) 85.5 Amps (NG)	100 Amps (Gas) 95 Amps (LP)	87.5 Amps (Gas) 83.33 Amps (LP) 75 Amps (NG)	87.5 Amps (Gas) 83.33 Amps (LP)	87.5 Amps (Gas) 83.33 Amps (LP)	37.50 Amps (Gas) 35.63 Amps (LP)
Running Amperage at 240V	50 Amps (Gas) 47.5 Amps (LP) 42.75 Amps (NG)	50 Amps (Gas) 47.5 Amps (LP) 42.75 Amps (NG)	50 Amps (Gas) 47.5 Amps (LP)	43.75 Amps (Gas) 41.67 Amps (LP) 37.5 Amps (NG)	43.75 Amps (Gas) 41.67 Amps (LP)	43.75 Amps (Gas) 41.67 Amps (LP)	18.75 Amps (Gas) 17.81 Amps (LP)
Outlets	50 Amp 240V (2) 120V GFCI (4)	50 Amp 240V (1) 30 Amp 240V (1) 30 Amp 240V (1) 120V GFCI (10)	50 Amp 240V (1) 30 Amp 240V (1) 30 Amp 240V (1) 120V GFCI (10)	50 Amp 120/240V (1) 30 Amp 120/240V (1) 20 Amp 120V GFCI (4)	50 Amp 120/240V (1) 30 Amp 120/240V (1) 20 Amp 120V GFCI (4)	50 Amp 240V (1) 30 Amp 240V (1) 30 Amp 240V (1) 120V GFCI (2) 8 Amp 12V DC (1)	30 Amp 120/240V (1) 20 Amp 120V (2) USB A (2)
Gasoline Runtime at 25% Load	17.9 Hrs	17.9 Hrs	17.9 Hrs	17 Hrs	17 Hrs	17 Hrs	19 Hrs
Gasoline Runtime at 50% Load	12 Hrs	12 Hrs	12 Hrs	8.5 Hrs	8.5 Hrs	8.5 Hrs	9 Hrs
Propane Runtime at 25% Load	12.5 Hrs (40 lb. tank)	12.5 Hrs (40 lb. tank)	12.5 Hrs (40 lb. tank)	13 Hrs (40 lb. tank)	13 Hrs (40 lb. tank)	13 Hrs (40 lb. tank)	15 Hrs (20 lb. Tank)
Propane Runtime at 50% Load	8.5 Hrs (40 lb. tank)	8.5 Hrs (40 lb. tank)	8.5 Hrs (40 lb. tank)	6.5 Hrs (40 lb. tank)	6.5 Hrs (40 lb. tank)	6.5 Hrs (40 lb. tank)	8 Hrs (20 lb. Tank)
Start Type (Remote, Push, Recoil)	Remote Push Button Recoil	Remote Push Button Recoil	Remote Push Button Recoil	Remote Push Button Recoil	Push Button Recoil	Push Button Recoil	Rocker Switch Recoil
Warranty	5 Years	5 Years	5 Years	5 Years	5 Years	3 Years	5 Years